SIEMENS

Data sheet 6ES7322-1BF01-0AA0

SIMATIC S7-300, Digital output SM 322, isolated, 8 DO, 24 V DC, 2A, 1x 20-pole



Figure similar

Supply voltage	
Load voltage L+	
• Rated value (DC)	24 V
• permissible range, lower limit (DC)	20.4 V
• permissible range, upper limit (DC)	28.8 V
Input current	
from load voltage L+ (without load), max.	60 mA
from backplane bus 5 V DC, max.	40 mA
Power loss	
Power loss, typ.	6.8 W
Digital outputs	
Number of digital outputs	8
Limitation of inductive shutdown voltage to	L+ (-48 V)
Switching capacity of the outputs	
• on lamp load, max.	10 W
Load resistance range	

Subject to change without notice
© Copyright Siemens

• lower limit	12 Ω
• upper limit	4 kΩ
Output voltage	
• for signal "1", min.	L+ (-0.8 V)
Output current	
• for signal "1" rated value	2 A
• for signal "1" minimum load current	5 mA
• for signal "0" residual current, max.	0.5 mA
Switching frequency	
• with resistive load, max.	100 Hz
• with inductive load, max.	0.5 Hz
• on lamp load, max.	10 Hz
Total current of the outputs (per group)	
horizontal installation	
— up to 40 °C, max.	4 A
— up to 60 °C, max.	4 A
vertical installation	
— up to 40 °C, max.	4 A
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m

Interrupts/diagnostics/status information	
Diagnostic functions	No
Alarms	
• Diagnostic alarm	No
Diagnostic messages	
• Wire-break	No
• Short-circuit	No
• Fuse blown	No
• missing load voltage	No
Diagnostics indication LED	
• Rated load voltage PWR (green)	No
• Fuse OK FSG (green)	No
• Status indicator digital output (green)	Yes; per channel

Potential separation	
Potential separation digital outputs	
• between the channels	Yes
• between the channels, in groups of	4
• between the channels and backplane bus	Yes; Optocoupler

Isolation	
Isolation tested with	500 V DC

Subject to change without notice
© Copyright Siemens

Connection method	
required front connector	20-pin

Dimensions	
Width	40 mm
Height	125 mm
Depth	120 mm

Weights	
Weight, approx.	190 g

last modified: 08/13/2018

Subject to change without notice
© Copyright Siemens